

2100 (250-1624)

Memory Upgrades

Faxback Doc. # 2504

256K and 4M SIMM memory used in this machine is no longer sold at Radio Shack.

256K x 9 and 4M x 9 SIMM memory can be ordered through Third Party Products.

1M x 9 SIMM Memory can be ordered at National Parts, Cat. # 250-5137.

System Memory Configurations:

MEMORY	BANK 0	BANK 1
1 MEG	4 256K x 9	
2 MEG	4 256K x 9	4 256K x 9
4 MEG	4 1M x 9	
5 MEG	4 256K x 9	4 1M x 9
	4 1M x 9	4 256K x 9
8 MEG	4 1M x 9	4 1M x 9
16 MEG	4 4M x 9	
17 MEG	4 256K x 9	4 4M x 9
	4 4M x 9	4 256K x 9
20 MEG	4 1M x 9	4 4M x 9
	4 4M x 9	4 1M x 9
32 MEG	4 4M x 9	4 4M x 9

NOTE: When you install more memory, you must change your system memory configuration in Setup. Please see faxback Doc. # 2505, SETUP, for instructions on how to update the CMOS RAM.

(smc-11/03/93)

□