DMP 300 (260-2818) Self-Test

Faxback Doc. # 4633

1. Press and hold the LINE/FORM button.

2. Turn on the printer.

The printer prints the ASCII 96 characters in various fonts programmed into the printer.

The self test printout also provides information about your printer.

Self Test Press and hold the Line/Form button while turning on the printer. The self test feature also shows: The Printer Model The Firmware Revision Number The Firmware Part Number The Character Generator Revision Number The Character Generator Part Number

(smm 07/27/93)